

Template on Card Setup

Specifications

Device:

BioEntry Plus and BioEntry W

Software Version:

BioStar 1.8 SE

Firmware:

BioEntry Plus - BEPI-OC – Firmware 1.51B_130503 (iClass TOC).bin

BioEntry W - BEWI-OC – Firmware 1.1_13610.bin

Steps

1. Create a new User. Note that if outputting wiegand to a third party control panel, the USER ID should be the corresponding badge number within your access control software.
2. Enroll the users fingerprint into the system by selecting “Add” followed by “Scan”. Click “Apply” to save.
3. Select the Card Tab, choose “iClass Template” as the card type, and click Card Management. (Make sure you have already enrolled a fingerprint).

Select “Write Card” and follow the on screen instructions.

Details | Fingerprints | Face | Face (Fusion) | **Card** | Access Control | T & A | Event

Card Type: iCLASS Template
Card No.: 3759341559 - 26034926 [Card Management]
 Bypass card

Card Issue History

Card Management [X]

Device ID: 543908080[192.168.1.6]

Smartcard Info
Serial No.: [] User ID: 1
User Name: Nick - Template on Card Security Level: Device Default
Access Group: Full Access [] Bypass card
Start Date: 1/1/2000 Expiry Date: 12/31/2030
Admin Level: Admin User

1st Template [] Duress
2nd Template [] Duress

[Read Card] [Write Card] [Format Card] [OK] [Cancel]

5. Enable Wiegand Output (Wiegand User). Note that the User ID number is the field that gets outputted if using this method.

Wiegand Mode

Wiegand Input

Wiegand Output